

FAST FIELDS INSTRUMENT
MODE : 25

3/21/97
REE

FAST FIELDS INSTRUMENT
MODE : 25

03/21/97
REE

2

SUMMARY

SLOW SURVEY: 12,288 bit/s
FAST SURVEY: 167,936 bit/s
BURST: 2,385,512 bit/s
SLOT: 14

DC FIELDS 3
LONG DURATION BURST 2
3-WIRE (Rev: 5)

A. SPHERE CONFIGURATION: Spheres in Current Mode: 6,7; Ne range 1 to 4x10⁴ cm⁻³

B. SLOW SURVEY

APID SUMMARY	DATA	SMPL/S	BITS/s
SVY0	V1-V4_S	32	512
APID 1032	V5-V8_S	32	512
2,048 bit/s	V9-V10_S	32	512
(1/128 max rate)	Mag1dc	8	128
	Mag2dc	8	128
	Mag3dc	8	128
	Therm	8	128
SVY1	V1-V2_S	32	512
APID 1033	V3-V4_S	32	512
2,048 bit/s	Ne6_S	32	512
(1/128 max rate)	Ne7_S	32	512
SVY2	Mag1ac_S	32	512
APID 1034	Mag2ac_S	32	512
2,048 bit/s	Mag3ac_S	32	512
(1/128 max rate)	V10_S	8	128
	V4_S	8	128
	V8_S	8	128
	LFF1	8	64
	LFF2	8	64
LFF1 set to V1-V4_HG. LFF2 set to V5-V8_HG.			
BBF	V1-V4_BBF	0	0
APID 1035	V5-V8_BBF	0	0
0 bit/s	Mag3ac_BBF	0	0
(OFF)	V9-V10_BBF	0	0
SFA_AVE	V1-V2_SFA	64	512
APID 1036	V5-V8_SFA	64	512
2,048 bit/s	Mag3ac_SFA	64	512
(Ave 64 sweeps)	V1-V4_TRK	64	512
Each Ch.: 1 swp/4s, 256 pts/sweep, Swp: 0 - 2 MHz.			
DSP	V5-V8HG_DSP	<128	<1,024
APID 1037	V1-V4TRK_DSP	<128	<1,024
4,096 bit/s	V1-V2HG_DSP	<128	<1,024
(Ave 128 sweeps)	Mag3ac_DSP	128	1,024
Each Ch.: 1 swp/4s, 512 pts/sweep, Swp: 0 - 16 kHz.			
HFQ	PD12	0	0
APID 1038	PD13	0	0
0 bit/s	PD14	0	0
(OFF)	PD23	0	0
	PD24	0	0
	PD34	0	0
	TRK_FRQ	0	0
	FRQ1	0	0
	FRQ2	0	0
	FRQ3	0	0
	FRQ4	0	0

* LFF, BBF, SFA, DSP, and PD are 8-bit words.

C. FAST SURVEY

APID SUMMARY	DATA	SMPL/S	BITS/s
SVY0	V1-V4_S	512	8,192
APID 1032	V5-V8_S	512	8,192
32,768 bit/s	V9-V10_S	512	8,192
(1/4 max rate)	Mag1dc	128	2,048
	Mag2dc	128	2,048
	Mag3dc	128	2,048
	Therm	128	2,048
SVY1	V1-V2_S	512	8,192
APID 1033	V2-V4_S	512	8,192
32,768 bit/s	Ne6_S	512	8,192
(1/4 max rate)	Ne7_S	512	8,192
SVY2	Mag1ac_S	512	8,192
APID 1034	Mag2ac_S	512	8,192
32,768 bit/s	Mag3ac_S	512	8,192
(1/4 max rate)	V10_S	128	2,048
	V4_S	128	2,048
	V8_S	128	2,048
	LFF1	128	1,024
	LFF2	128	1,024
LFF1 set to V1-V4_HG. LFF2 set to V5-V8_HG.			
BBF	V1-V4_BBF	512	4,096
APID 1035	V5-V8_BBF	512	4,096
16,384 bit/s	Mag3ac_BBF	512	4,096
(1/8 max rate)	V9-V10_BBF	512	4,096
SFA_AVE	V1-V2_SFA	128	1,024
APID 1036	V5-V8_SFA	128	1,024
4,096 bit/s	Mag3ac_SFA	128	1,024
(Ave 32 sweeps)	V1-V4_TRK	128	1,024
Each Ch.: 1 swp/2s, 256 pts/sweep, Swp: 0 - 2 MHz.			
DSP	V5-V8HG_DSP	1,024	8,192
APID 1037	V1-V4TRK_DSP	1,024	8,192
32,768 bit/s	V1-V2HG_DSP	1,024	8,192
(Ave 16 sweeps)	Mag3ac_DSP	1,024	8,192
Each Ch.: 2 swp/s, 512 pts/sweep, Swp: 0 - 16 kHz.			
HFQ	PD12	128	1,024
APID 1038	PD13	128	1,024
16,384 bit/s	PD14	128	1,024
(Only rate)	PD23	128	1,024
	PD24	128	1,024
	PD34	128	1,024
	TRK_FRQ	128	2,048
	FRQ1	128	2,048
	FRQ2	128	2,048
	FRQ3	128	2,048
	FRQ4	128	2,048

* LFF, BBF, SFA, DSP, and PD are 8-bit words.

D. BURST

APID SUMMARY	DATA	SMPL/S	BITS/s
ADC1	V1-V4HG_ADC1	0	0
APID 1048			
0 bit/s			
(OFF)			
ADC2	V5-V8HG_ADC2	32,768	524,288
APID 1049			
524,288 bit/s			
(Max rate)			
ADC3	V9-V10_ADC3	0	0
APID 1050			
0 bit/s			
(OFF)			
ADC4	V1-V4TRK_ADC4	32,768	524,288
APID 1051			
524,288 bit/s			
(Max rate)			
ADC5	V1-V2HG_ADC5	0	0
APID 1052			
0 bit/s			
(OFF)			
ADC6	Mag3ac_ADC6	0	0
APID 1053			
0 bit/s			
(OFF)			
ADC7	Mag1ac_ADC7a	8,192	131,072
APID 1054	Mag2ac_ADC7b	8,192	131,072
524,288 bit/s	Mag3ac_ADC7c	8,192	131,072
(Max rate)	D8_ADC7d	8,192	131,072
ADC8	V5-V8_ADC8a	8,192	131,072
APID 1055	V2-V4_ADC8b	8,192	131,072
524,288 bit/s	V9-V10_ADC8c	8,192	131,072
(Max rate)	V1-V4_ADC8d	8,192	131,072
WPC	All Quantities	307	157,288
APID 1056			
157,288 bit/s			
(Max rate)			
Field input: V1-V4_HF (0.2 - 2 MHz)			
V5-V8_HF (0.2 - 2 MHz)			
BCOR OFF			
SFA	V1-V2_SFA	4,096	32,768
APID 1057	V5-V8_SFA	4,096	32,768
131,072 bit/s	Mag3ac_SFA	4,096	32,768
(1/2 rate)	V1-V4_TRK	4,096	32,768
Each Ch.: 16 swp/s, 256 pts/sweep, Swp: 0 - 2 MHz.			
Track Frequency - V1-V4 Zero Crossing.			
HSBM	V1-V2_HSBM		
APID 1058	V5-V8_HSBM		
Memory allocation: Mag3ac_HSBM			
20,971,520 bytes	V9-V10_HSBM		
Sample rate: 0.5 us.			
Buffer size: 2,621,440 bytes.			
Triga=BBF1. TrigB=LFF2.			
PROC MODE =15, OL = 7, 4 second latency.			
(Capture during fast survey or burst.)			

E. MODE SET UP

POWER			
Command sequence (setbit):			
F9 0 :	System 7	Fields survey	ON
F8 14 :	System 4	Fluxgate	ON
F8 6 :	System 6	BEB1,2; Spheres 1,2,3,4.	ON
F8 7 :	System 23	BEB3,4; Spheres 5,6,7,8.	ON
F8 8 :	System 24	AXBEB; Spheres 9,10.	ON
F9 1 :	System 8	Fields LF analog	ON
F8 15 :	System 3	Search Coil	ON
F9 2 :	System 9	Fields HF analog, Osc.	ON
F9 3 :	System 10	SFA	ON
F9 4 :	System 11	WPC, BFF, HFQ	ON
** :	System 12	HSEB	ON
** :	System 13	DSP	ON
** :	System 14	DSP ROM	ON
** -	Driver turn on.	HSEB:.61000001. DSP:.60000001.	
BEB1	IBIAS2	-6.25 nA	IBIAS3 0 nA
400078	STUB2	+300 mV	490080 STUB3 0.0 V
410090	IBIAS1	-6.25 nA	4A0080 IBIAS4 0 nA
420078	STUB1	+300 mV	4B0080 STUB4 0.0 V
430090	GUARD	0.0 V	4C0000 GUARD 0.0 V
440000	SPH2	V_Mode	4D0001 SPH3 V_Mode
450001			
BEB3	VBIAS6	+15 V	5B0000 VBIAS7 +15 V
5000C0	STUB6	+300 mV	590090 STUB7 +300 mV
510090	IBIAS5	-6.25 nA	5A0078 IBIAS8 -6.25 nA
520078	STUB5	+300 mV	5B0090 STUB8 +300 mV
530090	GUARD	0.0 V	5C0000 GUARD 0.0 V
540000	SPH6	GL/I_Mode	5D000A SPH7 GL/I_Mode
55000A			
FORMATTER	APID ON/OFF		AXBEB
D8283D	Rate SFA,ADC,BBF		600080 IBIAS9 0 nA
D90067	CLRBIT D5 8		610080 IBIAS10 0 nA
			620005 V9, V10 V_Mode
ANALOG A/B	SVY 1/128 SPEED		ANALOG C
800006	ADC1 to ADC 4		A00000 ANC, BCOR TRIG
823102	ADC5 to ADC 8		A16EA2 ESA HEAD POS
830A9D	ADC7 MUX		A20000 BCOR OFF
8405AC	ADC8 MUX		A40000 FREQ-T
8500A1	TRIGGERS		DSP
860009	ANB, SFATRK		9080E8 ADC1 to ADC6
880C00			948007 AVERAGE 2^7
SFA	SWP to 2MHz		HSBM
A8052A	HFDDIST		98B803 MSZ=7, 2MS/s
A973FB	SFA TRACK		99B8A0 Min Lvl LFF2, BBF1
AA2600			9A8803 Sel BBF1, LFF2
SLOW -> FAST			FAST -> SLOW
D803D			D90067
D90066			800006
908002			9080E8
948004			948007
disks/plasmal/home/ree/fast/modes/frm3/mode025.frm			
Rev 5: Higher ADC rate than mode 26.			