

FAST FIELDS INSTRUMENT
MODE : 42

02/18/99
REE

FAST FIELDS INSTRUMENT
MODE : 42

02/18/99
REE

2

SUMMARY

SLOW SURVEY: 14,366 bit/s
FAST SURVEY: 491,520 bit/s
BURST: 3,316,122 bit/s
SLOT: 12

BACKUP :Low Alt - Gen Ci
HIGH RES, B_4k, HG=1/4
3-Wire (Rev: 6)

A. SPHERE CONFIGURATION: Spheres in Current Mode: 6,7; Ne range 1 to 4x10⁴ cm⁻³

B. SLOW SURVEY

APID SUMMARY	DATA	SMPL/S	BITS/s
SVY0	V1-V4_S	32	512
APID 1032	V5-V8_S	32	512
2,048 bit/s	V9-V10_S	32	512
(1/128 max rate)	Mag1dc	8	128
	Mag2dc	8	128
	Mag3dc	8	128
	Therm	8	128
SVY1	V1-V2_S	32	512
APID 1033	V2-V4_S	32	512
2,048 bit/s	Ne6_S	32	512
(1/128 max rate)	Ne7_S	32	512
SVY2	Mag1ac_S	32	512
APID 1034	Mag2ac_S	32	512
2,048 bit/s	Mag3ac_S	32	512
(1/128 max rate)	V10_S	8	128
	V4_S	8	128
	V8_S	8	128
	LFF1	8	64
	LFF2	8	64
LFF1 set to V1-V4_HG. LFF2 set to V5-V8_HG.			
BBF	V1-V4_BBF	0	0
APID 1035	V5-V8_BBF	0	0
0 bit/s	Mag3ac_BBF	0	0
(OFF)	V9-V10_BBF	0	0
SFA_AVE	V1-V4_SFA	64	512
APID 1036	V5-V8_SFA	64	512
2,048 bit/s	Mag3ac_SFA	64	512
(Ave 64 sweeps)	V9-V10_4MHz	64	512
Each Ch.: 1 swp/4s, 256 pts/sweep, Swp: 0 - 2 MHz.			
DSP	V1-V4HG_DSP	<128	<1,024
APID 1037	V5-V8HG_DSP	<128	<1,024
6,144 bit/s	V1-V2HG_DSP	<128	<1,024
(Ave 128 sweeps)	Mag3ac_DSP	128	1,024
Each Ch.: 1 swp/4s, 512 pts/sweep, Swp: 0 - 16 kHz.			
HFQ	PD12	0	0
APID 1038	PD13	0	0
0 bit/s	PD14	0	0
(OFF)	PD23	0	0
	PD24	0	0
	PD34	0	0
	TRK_FRQ	0	0
	FRQ1	0	0
	FRQ2	0	0
	FRQ3	0	0
	FRQ4	0	0

* LFF, BBF, SFA, DSP, and PD are 8-bit words.

C. FAST SURVEY

APID SUMMARY	DATA	SMPL/S	BITS/s
SVY0	V1-V4_S	2,048	32,768
APID 1032	V5-V8_S	2,048	32,768
131,072 bit/s	V9-V10_S	2,048	32,768
(Max rate)	Mag1dc	512	8,196
	Mag2dc	512	8,196
	Mag3dc	512	8,196
	Therm	512	8,196
SVY1	V1-V2_S	2,048	32,768
APID 1033	V2-V4_S	2,048	32,768
131,072 bit/s	Ne6_S	2,048	32,768
(Max rate)	Ne7_S	2,048	32,768
SVY2	Mag1ac_S	2,048	32,768
APID 1034	Mag2ac_S	2,048	32,768
131,072 bit/s	Mag3ac_S	2,048	32,768
(Max rate)	V10_S	512	8,196
	V4_S	512	8,196
	V8_S	512	8,196
	LFF1	512	4,092
	LFF2	512	4,092
LFF1 set to V1-V4_HG. LFF2 set to V5-V8_HG.			
BBF	V1-V4_BBF	512	4,096
APID 1035	V5-V8_BBF	512	4,096
16,384 bit/s	Mag3ac_BBF	512	4,096
(1/8 max rate)	V9-V10_BBF	512	4,096
SFA_AVE	V1-V4_SFA	512	4,096
APID 1036	V5-V8_SFA	512	4,096
16,384 bit/s	Mag3ac_SFA	512	4,096
(Ave 8 sweeps)	V9-V10_4MHz	512	4,096
Each Ch.: 2 swp/s, 256 pts/sweep, Swp: 0 - 2 MHz.			
DSP	V1-V4HG_DSP	1,024	8,192
APID 1037	V5-V8HG_DSP	1,024	8,192
49,152 bit/s	V1-V2HG_DSP	1,024	8,192
(Ave 16 sweeps)	Mag3ac_DSP	1,024	8,192
Each Ch.: 2 swp/s, 512 pts/sweep, Swp: 0 - 16 kHz.			
HFQ	PD12	128	1,024
APID 1038	PD13	128	1,024
16,384 bit/s	PD14	128	1,024
(Only rate)	PD23	128	1,024
	PD24	128	1,024
	PD34	128	1,024
	TRK_FRQ	128	2,048
	FRQ1	128	2,048
	FRQ2	128	2,048
	FRQ3	128	2,048
	FRQ4	128	2,048

* LFF, BBF, SFA, DSP, and PD are 8-bit words.

D. BURST

APID SUMMARY	DATA	SMPL/S	BITS/s
ADC1	V1-V4HG_ADC1	32,768	524,288
APID 1048			
524,288 bit/s			
(Max rate)			
ADC2	V5-V8HG_ADC2	32,768	524,288
APID 1049			
524,288 bit/s			
(Max rate)			
ADC3	SVY_BAC	0	0
APID 1050			
OFF			
ADC4	XXX	0	0
APID 1051			
OFF			
ADC5	V1-V2HG_ADC5	32,768	524,288
APID 1052			
524,288 bit/s			
(Max rate)			
ADC6	Mag3ac_ADC6	32,768	524,288
APID 1053			
524,288 bit/s			
(Max rate)			
ADC7	Mag1ac_ADC7a	8,192	131,072
APID 1054	Mag2ac_ADC7b	8,192	131,072
524,288 bit/s	V1-V2_ADC7c	8,192	131,072
(Max rate)	D8_ADC7d	8,192	131,072
ADC8	Ne7_ADC8a	8,192	131,072
APID 1055	V9-V10_ADC8b	8,192	131,072
524,288 bit/s	V5-V8_ADC8c	8,192	131,072
(Max rate)	V1-V4_ADC8d	8,192	131,072
WPC	All Quantities	307	39,322
APID 1056			
39,322 bit/s			
(1/4 rate)			
Field input: V1-V4_LF (1-16 kHz)			
V5-V8_LF (1-16 kHz)			
BCOR OFF			
SFA	V1-V4_SFA	4,096	32,768
APID 1057	V5-V8_SFA	4,096	32,768
131,072 bit/s	Mag3ac_SFA	4,096	32,768
(1/2 rate)	V9-V10_4MHzA	4,096	32,768
Each Ch.: 16 swp/s, 256 pts/sweep, Swp: 0 - 2 MHz.			
Track Frequency - V1-V4 Zero Crossing.			
HSBM	V1-V4_HSBM		
APID 1058	V5-V8_HSBM		
Memory allocation: Mag3ac_HSBM			
20,971,520 bytes	V9-V10_HSBM		
Sample rate: 0.5 us.			
Buffer size: 655,360 bytes.			
Triga=BBF1. TrigB=LFF2.			
PROC MODE =15, OL = 7, 4 second latency.			
(Capture during fast survey or burst.)			

E. MODE SET UP

POWER			
Command sequence (setbit):			
F9 0 :	System 7	Fields survey	ON
F8 14 :	System 4	Fluxgate	ON
F8 6 :	System 6	BEB1,2; Spheres 1,2,3,4.	ON
F8 7 :	System 23	BEB3,4; Spheres 5,6,7,8.	ON
F8 8 :	System 24	AXBEB; Spheres 9,10.	ON
F9 1 :	System 8	Fields LF analog	ON
F8 15 :	System 3	Search Coil	ON
F9 2 :	System 9	Fields HF analog, Osc.	ON
F9 3 :	System 10	SFA	ON
F9 4 :	System 11	WPC, BFF, HFQ	ON
** :	System 12	HSEB	ON
** :	System 13	DSP	ON
** :	System 14	DSP ROM	ON
** - Driver turn on. HSEB:.61000001. DSP:.60000001.			
BEB1	IBIAS2	-12.5 nA	IBIAS3 0 nA
410080	STUB2	+150 mV	490080 STUB3 0.0 V
420070	IBIAS1	-12.5 nA	4A0080 IBIAS4 0 nA
430088	STUB1	+150 mV	4B0080 STUB4 0.0 V
440080	GUARD	-5.0 V	4C0000 GUARD 0 V
450001	SPH2	V_Mode	4D0001 SPH3 V_Mode
BEB3	VBIAS6	+15 V	BEB4 VBIAS7 +15 V
510088	STUB6	0.0 V	590088 STUB7 0.0 V
520070	IBIAS5	-12.5nA	5A0070 IBIAS8 -12.5nA
530088	STUB5	0.0 V	5B0088 STUB8 0.0 V
540080	GUARD	-5.0 V	5C0080 GUARD -5.0 V
55000A	SPH6	GL/I_Mode	5D000A SPH7 GL/I_Mode
FORMATTER	APID ON/OFF	AXBEB	
D8280C	D8280C	600080	IBIAS9 0 nA
D90067	Rate SFA,ADC,BBF	610080	IBIAS10 0 nA
CLRBIT D5 8		620005	V9, V10 V_Mode
ANALOG A/B		ANALOG C	
800026	SVY 1/128 SPEED	A00006	ANC, BCOR TRIG
823102	ADC1 to ADC 4	A16EA2	ESA HEAD POS
830A9D	ADC5 to ADC 8	A20000	BCOR OFF
84042C	ADC7 MUX	A40000	FREQ-T
850055	ADC8 MUX	DSP	
860009	TRIGGERS	9080CC	ADC1 to ADC6
881800	ANB, SFATRK	948007	AVERAGE 2^7
SFA	A80D20	SWP to 2MHz	HSBM
APID 1057	A937FC	HPDIST	98B803
131,072 bit/s	AA2600	SFA TRACK	MSZ=7, 2MS/s
(1/2 rate)			99B898
Each Ch.: 16 swp/s, 256 pts/sweep, Swp: 0 - 2 MHz.			2.5 V TMIN
Track Frequency - V1-V4 Zero Crossing.			9A8803
HSBM			Sel BBF1,LFF2
APID 1058			
Memory allocation: Mag3ac_HSBM			
20,971,520 bytes			
Sample rate: 0.5 us.			
Buffer size: 655,360 bytes.			
Triga=BBF1. TrigB=LFF2.			
PROC MODE =15, OL = 7, 4 second latency.			
(Capture during fast survey or burst.)			
SLOW -> FAST		FAST -> SLOW	
D8000C		D8280C	
D90064		D90067	
800026		800026	
9080CC		9080CC	
948004		948007	
-ree/fast/modes/fm3/mode048.rm			
Rev. 5 - SVY BAC.			
- HG at 1/4.			
- SFA V910 @ 4 MHz.			
- HSBM No Retrig tpos 1/4			
- WPC 1/4 in LF.			